



TECHNICAL SPECIFICATION

Technical Service Department,
JSP Ltd., Worsham Mill, Minster
Lovell, Oxford, OX29 0TA
Tel.: 01993 824000
Fax: 01993 824422

Lamp Batteries

Type: H4R25 / 996 (Or equivalent)

Voltage: 6V

Battery Life (Hours) The Battery Life for each type of lamp and circuit has been tested. From the results gained, JSP would expect that in normal conditions the battery life to be on average, the following:

Metrolite / Plastiflash / Steelflash (Twin Battery Lamp)

FNPC	FPC	SNPC	SPC
110	500	120	175

PowerLite (Twin Battery Lamp)

FNPC	FPC	SNPC	SPC
375	650	150	175

MaxiLite (Twin Battery Lamp)

FNPC	FPC	SNPC	SPC	Xenon FNPC	Xenon FPC
375	650	150	175	175	325

Microlite (Single Battery Lamp)

FNPC	FPC	SNPC	SPC
40	65	65	75

Minilite (Single Battery Lamp)

FNPC	FPC	SNPC	SPC
35	50	50	65

Instructions For Use: Remove spent battery (batteries). Refit the required number. Ensure they are aligned as per markings on lamp used.

Disposal: Dispose of the spent battery in accordance with local regulations.

Notes:

FNPC = Flashing Non-Photo Cell

FPC = Flashing Photo Cell

SNPC = Static Non-Photo Cell

SPC = Static Photo Cell